

Sticklers™ Fiber Optic Splice & Connector Cleaner

Cleaning Fluid

Product Features:

- Fast evaporating, no residue optical grade cleaning fluid for cleaning fibre
- Not regulated for transport by land, sea or air
- Nonflammable, nontoxic
- Dissipates electrostatic charges
- Compliant with Ventura County Air Pollution Control District Rule 74.6; reference 74.6; B.2.C
- ROHS and REACH compliant






Typical Cleaning Applications:


Pigtails and bare fibres for fusion splicing
Ribbon fibres for mass fusion splicing
Splicing plastic optical fibres and connectors
Ceramic and composite ferrules
Most glass and plastic photonic lenses
Suitable cleaning fluid for tool kits



Patented Triton™ dispenser enables 3 cleaning methods

Video:
[How to Use Fibre Optic Splice & Connector Cleaner](#)
 @ SticklersCleaners.com

Packaging:	85 g (3oz) NET fluid weight	284 g (10 oz) NET fluid weight
Part Number	MCC-POC03M 	MCC-POC10M
Cleans Per Can	650+	2500+
NSN #	6850-01-592-9391	N/A
REACH #	01-2119899252-29-0001	
Can Specifications	<ul style="list-style-type: none"> • 120 grams - total can weight • 39 mm OD x 130 mm H 	<ul style="list-style-type: none"> • 374 grams - total can weight • 66 mm OD x 172 mm H
Case Dimensions	203 mm L x 152 mm W x 152 mm H	305 mm L x 229 mm W x 178 mm H
Case Quantity	12 Cans per Case	12 Cans per Case
GHS/HCS Pictogram	Not Applicable	Not Applicable
Recycle Symbol		

 85 g (3 oz) can (MCC-POC03M) comes in hassle-free travel size packaging.



Sticklers™ Fibre Optic Splice & Connector Cleaner conforms to the following Fibre Optic Industry Standards:

Industry Standards	Section	Description
ANSI/TIA 455-240 2009		Fibre Optic Connector End-Face Cleaning Evaluation
ANSI/TIA 568.3D-2016	E.3.5	Connector End-Face Cleaning
ARINC 805-4		Fibre Optic Test Procedures
ARINC 806-5		Fibre Optic Installation & Maintenance
AT&T ATT-TP-76461		Inspecting & Cleaning End-Faces
Cisco Systems Doc: 51837		Inspecting & Cleaning Procedures for Fibre Connectors
IBM SY27-2597-15		Cleaning End-Faces for Maintaining Fibre Links
IEC 61300-3-35	5.3	End-Face Cleaning
IEC 61627-1	7.8	Acceptable Wet-Dry End-Face Cleaning
IEC 62627-1	9.3	Procedure Wet-Dry Cleaning w/ Reel Type Cleaners
IEC 61627-1	9.4	Procedure Wet-Dry Cleaning w/ Sticks & Clickers
IPC 8497-1	7.3.6	Cleaning Fluids & Wet Swabs & Face Cleaning
IPC 8497-1	10	Minimizing Electrostatic Charge Effect
NASA-STD 8739.5A	8	Cleaning Workmanship Standards
SAE AIR6031		End-Face Cleaning
SAE ARP 6283	8.6	Approved Cleaning Solvents
SAE ARP 6283	9.1.1	Wet-Dry Cassette Cleaning
Telcordia GR2923 CORE Issue 2		End-Face Cleaning
Telcordia GR765-CORE	4.6	Fusion Splicing Materials & Consumables Criteria
Verizon VZ.TRP.9461	5.0	End-Face Cleaning



MicroCare, LLC
 595 John Downey Drive
 New Britain, CT 06051 USA
 CAGE: OATV9
 Tel: +1 860 827 0626
 Toll Free: 1 800 638 0125
 Email: TechSupport@MicroCare.com

MicroCare Europe BVBA
 Vekestraat 29 B11
 Industriezone 't Sas
 1910 Kampenhout, Belgium
 Tel: +32 2 251 95 05
 Email: EuroSales@MicroCare.com

MicroCare U.K. Ltd
 Seven Hills Business Centre
 South Street, Morley
 Leeds, United Kingdom
 LS27 8AT
 Tel: +44 (0) 113 3609019
 Email: mcceurope@microcare.com

MicroCare Asia Pte Ltd
 102E Pasir Panjang Road
 #03-01 Citilink Warehouse Complex
 Singapore 118529
 Tel: +65 6271 0182
 Email: TechSupport@MicroCare.sg